

RADIO MARELLI. — 8A05- 8F15.

VALORI DEI COMPONENTI

=====

CONDENSATORI

C1-C2	2 X 120 pF
C3-C11	compens.
C12	10 pF
C13	270 pF
C14	168 pF
C15	6,4 pF
C17-C38	2000 pF
C18	0,1 MF
C19-C39	20000 pF
C20-C21-C22=C27/28	164 pF
C23-C24-C25	125 pF

C26	180 pF
C29	14 pF
C30-C33-C37	16000 pF
C40	10000 pF
C41-C42(8A05)	5000 pF
C43	25 MF
C44	5/10 MF
C45 (e 49 nel 8F15)	15 MF
C46	15 MF
Nel mod. 8F15 C41 e di 10 MF	

RESISTENZE

R1	1,6 M 1/2 W
R2(8A05)	220 ohm 1 W
R2(8F15)	200 ohm 2 W
R3	1600 ohm 1/2 W
R4	0,5 M 1/2 W
R5	0,25 M 1/2 W
R6=11=13	50000 ohm 1/2 W
R18=21	50000 ohm 1/2 W

R12-14	250 ohm 1/2 W
R15	1000 ohm 1 W
R16(8A05)	1600 ohm 1 W
R16(8F15)	32000 ohm 1 W
R17	1 M 1/2 W
R19	0,5 M poten.
R10	4000 ohm 1/2 W
R20	50 ohm 1/4 W

Vedere gli schemi nella Tavola quinta.